

EMPREX™

ENHANCE YOUR DIGITAL LIFESTYLE

www.emprex.com

AWV-699B Emprex 5.8GHz AV Sender



Features:

- 5.8GHz Wireless transmitter and receiver with 7 selectable channels
- Transmitting and receiving of crisp video and hi-fi stereo even through walls
- Long transmission range - up to 400 feet in clear line of sight
- Built in IR Remote extender for extending control range of IR remotes up to 100 feet even through walls
- New improved design with easier setup and more professional outlook
- Also compatible with previous model additional receiver kits AWV-698B-R

Box Contents:

- Transmitter (Tx) and Receiver (Rx)
- IR Extender cable for transmitter
- Power Adaptors x2
- RCA (Scart) to 3.5mm AV Adaptor x2
- Instruction Manual

Specifications:

- Frequency Range: 5725~5875 MHz
- Antenna Type: Omni-directional Dipole
- Channel Select: PLL Synth 7CH @ 433MHz
- Transmitter Output Power: 12 dBm
- Video/Audio Mod/Demod Type: FM-FM
- Transmitter Antenna Type: Dipole Antenna
- Video Polarity: Negative
- Receiving Sensitivity: -85 dBm (Typ)
- Supply Voltage: DC + 9V/300 mA
- Receiver Antenna Type: Patch Antenna
- Built in IR Remote Extender
- Operating Frequency: 433.92 MHz
- Power on indicator: Green LED

Packing Details:

- Product Dims: 12.4(L) x 8.4(H) x 10.9(W) cm (each)
- Product Weight: 190 grams (each)
- Box Dims: 26.2(L) x 9.3(H) x 18(W) cm
- Box Weight: 1.07 Kg
- Box Per Carton: 8
- Carton Dims: 40.7(L) x 37.7(H) x 27.9(W) cm
- Carton Weight: 9.2 Kg
- Cartons Per Pallet: 64
- EAN Code: 4710836937017

Product Certifications:



For details on this and a wide range of exciting products please visit us @

www.emprex.com

Please note products may look different from above and the specifications are subject to change without prior notice